

SLA-100-360 Power

Maximum output voltage 90Vp-p($\pm 45Vp$)

Maximum output current 8Ap

Bandwidth (-3dB) DC~100kHz

Slew rate $\geq 20V/\mu s$



Overview

The SLA-100-360 is an ideal power amplifier for amplifying AC and DC signals. Maximum output 360Wp power, can drive power type load. The gain control can be adjusted, and the common Settings can be saved with one key, providing you with a convenient and simple choice of operation. It can be used with the mainstream signal generator to achieve perfect signal amplification.

Input

The input is BNC interface. Input resistance 50 Ω , 10K Ω two optional, perfect match high and low internal resistance signal source.

Output

Output banana socket, the maximum output voltage 90Vp-p($\pm 45Vp$), the maximum output current 8Ap.

LCD Panels Display

Operation panel LCD display, device status and parameters dynamic display, interactive interface at a glance, simple and easy to understand.

Voltage Gain

The voltage gain is adjustable from 0 to 30 times, which can be divided into coarse adjustment (1step) and fine adjustment (0.1step). Combined with the display of the LCD panel gain, the voltage can be quickly adjusted to the required value.

Application

- Electronic experiments in universities
- MEMS
- Ultrasonic tests
- To drive the electromagnetic field
- Used for piezoelectric ceramic drive

Specifications

| | |
|---|---|
| Model | SLA-100-360 |
| Form of output | Single output |
| Bandwidth (-3dB) | DC~100kHz |
| Maximum output voltage | 90Vp-p ($\pm 45Vp$) |
| | 4Ap (DC~50Hz) |
| Maximum output current | 8Ap (>50Hz) |
| Maximum output power | 360Wp |
| Fuse | 8A/250V |
| Voltage gain | x0~30 (0.1 step/1 step) |
| | $\geq 10.75\Omega$ (DC~50Hz) |
| Upper limit of load R_L | $\geq 5.13\Omega$ (>50Hz) |
| Slew rate | $\geq 20V/\mu s$ |
| Output resistance | 0.5 Ω /50 Ω (customizable) |
| Input resistance | 50 Ω /10k Ω |
| Voltage monitor | 50mV/V |
| Current monitor | 200mV/A |
| Output voltage error | $\leq \pm 3\%$ FS@1kHz |
| Total harmonic distortion (THD) | $\leq 0.5\% @ 1kHz$, 90Vp-p |
| Zero-point drift of output voltage | $\leq \pm 0.3V$ |
| Signal-noise ratio(SNR) | $\geq 80dB$ |
| Output connector | 4mm banana socket |
| Protection | Overcurrent protection |
| Signal ground | Connected with the grounding of the shell and the power line. |

Other

| | |
|------------------------------|---------------------------------|
| Supply voltage | AC110~240V, 50/60Hz |
| Operating temperature | 0°C ~ 45°C |
| Storage temperature | -20°C ~ 50°C |
| Humidity | $\leq 80\%$ RH, no condensation |
| Warranty | 3 years |
| Size | 440*163*470mm (w * h * d) |

Order

| | |
|--------------------|--|
| Model | SLA-100-360 Power Amplifier |
| Parameters | DC~100kHz (-3dB) |
| Accessories | *1 three-core power cord, *3 BNC wires, *1 set of output wires, *1 safety tube, product specification, certificate, packing list and factory test report each. |
| Contact | sales@salukitec.com |