

SCKCL09-3.5 Mechanical Calibration Kit

(DC to 9GHz, 3.5mm)

Model								
SCKCL09-3.5								
Type								
3.5mm								
	C0 (F*10-15)	C1 (F*10-27/Hz)	C2 (F*10-36/Hz2)	C3 (F*10-45/Hz3)	Display (ps)	Z0 (Ω)	Loss (G Ω /s)	Frequency (GHz)
Open (f)	49.433	-310.13	23.168	-0.15966	29.243	50	2.2	0-999
Open (m)	49.433	-310.13	23.168	-0.15966	29.243	50	2.2	0-999
	C0 (H*10-12)	C1 (H*10-24/Hz)	C2 (H*10-33/Hz2)	C3 (H*10-42/Hz3)	Display (ps)	Z0 (Ω)	Loss (G Ω /s)	Frequency (GHz)
Short (f)	2.0765	-108.54	2.1705	-0.01	31.785	50	2.36	0-999
Short (m)	2.0765	-108.54	2.1705	-0.01	31.785	50	2.36	0-999